



Descriptions

- * With mp3/TUNER/Bluetooth functions.
- * Apply in small places which need Public address system.

Features

- * Standard rack mounted design (1U), SMT design.
- * With mp3/TUNER/Bluetooth module, Digital screen displaying the current music from USB.
- * With mp3/TUNER/Bluetooth remote control function.
- * 1 EMC input, 2 AUX input, 4 MIC input.
- * Channel priority: EMC > MIC1 > MIC2, MIC3, AUX1, AUX2.
- * Each channel has volume control function, master volume controls and bass/treble tone control.
- * Has level indicator, overload and protection indicator.
- * With High temp, overload & short-circuit protection.
- * 2 output modes: 100V, 70V (non-Bridged mode).
- * High energy and energy saving design of power supply and efficient power amplifier.
- * Wide voltage power supply: 180V - 240 V can work normally.

Specifications

Model	T-120TB
Output Terminal	70V, 100V
Output Power	120W
The Input Sensitivity and Impedance	MIC1, 2, 3, 4input: 5mV/600Ω Unbalanced 6.3 connector AUX1, 2 input: 350mV/10KΩ Unbalanced RCA connector EMC input: 775mV/10KΩ Unbalanced 6.3 connector
Output Sensitivity & Source Impedance	MIX OUT:1000mV/470Ω Unbalanced RCA connector
Tone	Bass: ±10dB at 100Hz Treble: ±10dB at 10KHz
Frequency Response	50Hz~16KHz (+1dB, -3dB)
SNR	MIC1, 2, 3: 66dB; AUX1, 2: 80dB
THD	Less than 0.5% (at 1KHz, 1/3 rated power)
Mute Control	EMC has highest priority MIC 1 priority over MIC2-4, AUX1-2 audio input,
Channel Crosstalk Attenuation	≥50dB
Heat Dissipation	Flank in and rear panel out to force fan cooling, fan starts when amplifier turned on, infinitely variable speeds
Protection	Over-heat, overload, short circuit, etc
Power Supply	~220-240V 50/60Hz
Power Consumption	180W
Dimension	484 x 260 x 44mm
Weight	4.5Kg

Rear Panel

