

SHURE®

LEGENDARY
PERFORMANCE™



SLX® WIRELESS SYSTEMS

**SMART, HARD-WORKING
WIRELESS.**

SLX® Wireless Microphone Systems

EVERWHERE WIRELESS.

Whether it's for a sound installation or a working band on the road, audio professionals need powerful wireless tools that can be set up quickly and used confidently. Shure's rugged SLX Wireless Systems exceed these demands with innovative automatic setup features, exceptional wireless clarity and legendary Shure microphones. Supporting up to 20 compatible systems across multiple UHF frequency bands, SLX smoothly integrates into houses of worship, lecture halls, conference rooms and mobile gear cases.

Shure's patented Audio Reference Companding


Delivers crystal-clear audio transmission, far superior to conventional wireless technology

Auto Frequency Selection

Locates a clear channel instantly

Auto Transmitter Setup

Infrared link automatically syncs the transmitter and receiver



Wireless Receiver

- Detachable 1/4 wave antennas
- Backlit LCD
- Rack-mount hardware included
- 1/4" and XLR audio outputs
- Frequency and power lockout
- Volume control on rear of unit
- Rugged metal construction

Handheld or Bodypack Transmitter

- Choice of Shure handheld microphones
- Bodypack works with headworn, lavalier and instrument microphones and cables
- Timed backlit LCD
- Frequency and power lockout
- 2 AA batteries (included) provide 8 hours of continuous use
- 100m (300 ft.) operating range

Available System Options

Handheld



SM58®
SM86
BETA 58A®

BETA 87A
BETA 87C

Systems include:

SLX4 Diversity Receiver and a choice of Handheld Microphone Transmitter.

SLX24/SM58
SLX24/SM86
SLX24/BETA58

SLX24/BETA87A
SLX24/BETA87C

Lavalier



WL93
WL184
WL185

Systems include:

SLX4 Diversity Receiver, SLX1 Bodypack Transmitter and a choice of Microphone or Guitar/Bass Cable.

SLX14/93 SLX14/SM35 SLX14 SLX14/BETA98H
SLX14/84 SLX14/85

Headworn



SM35*

*Available in select regions.

Guitar



WA302

Instrument



WB98H/C

Combo



SM58®
WL185



Wireless Microflex® Boundary/Gooseneck



MX690



MX405
with **MX890**



MX410
with **MX890**

Microflex Microphones are sold as components only.

Optional Accessories

- UA221** Passive Antenna Splitter
- UA505** Remote Mount Kit for ½ wave antennas
- UA820** ½ Wave Antennas
- UA825** 25' cable for ½ wave antennas
- UA844SWB** Antenna/Power Distribution System
- UA850** 50' cable for ½ wave antennas
- UA830** Active Remote Antenna Kit (UA844 required)
- UA870** Active Directional Antenna (UA844 required)
- WA610** Universal Hard Carrying Case transmitter

Optional Logic Functionality

A logic circuit and associated block connector is provided on the SLX4L receiver, designed to function optimally with software echo cancellers and provide remote monitoring of transmitter battery life. Supported models include MX690, MX890, and SLX4L receiver.

SLX4L Wireless Receiver with Logic

MX690 Wireless Microflex® Boundary Microphone

MX890 Wireless Microflex® Desktop Base

System Specifications

NOTE: All specifications are subject to change.

Frequency Range and Transmitter Output Level

Band	Range	SLX1/SLX2	MX690/ MX890
H5	518–542 MHz	30 mW	10 mW
J3	572–596 MHz	28 mW	28 mW
L4	638–662 MHz	30 mW	10 mW
P4	702–726 MHz	30 mW	10 mW
R5	800–820 MHz	20 mW	10 mW
S6	838–865 MHz	10 mW	10 mW
JB	806–810 MHz	10 mW	10 mW
Q4	740–752 MHz	10 mW	10 mW
R13	794–806 MHz	20 mW	10 mW
G4	470–494 MHz	30 mW	10 mW
G5	494–518 MHz	30 mW	10 mW

Operating Range:

30–100 m (100–300 ft.) under typical conditions, depending on transmitter type

Note: actual range depends on RF signal absorption, reflection, and interference.

Audio Frequency Response:

Minimum: 45 Hz, Maximum: 15 kHz (± 2 dB)

Total Harmonic Distortion:

0.5%, typical (ref. ± 38 kHz deviation, 1 kHz tone)

Dynamic Range:

>100 dB A-weighted

Operating Temperature Range:

-18°C (0°F) to +50°C (+122°F)

Note: battery characteristics may limit this range.

Transmitter Audio Polarity:

Positive pressure on microphone diaphragm (or positive voltage applied to tip of WA302 phone plug) produces positive voltage on pin 2 (with respect to pin 3 of low impedance output) and the tip of the high impedance $\frac{1}{4}$ -inch output.

NOTE: This radio apparatus may be capable of operating on some frequencies not authorized in your region. Please contact your national authority to obtain information on authorized frequencies and output power levels for wireless microphone products in your region.



Audio
Reference
Companding

- No “breathing” noise
- Lower noise floor
- More headroom - won’t clip as easily
- Clearer sound at all audio levels
- Sounds more like a wired mic

Component Specifications

Receiver	Handheld Transmitter	Bodypack Transmitter
SLX4 Receiver Front	SLX4 Handheld Transmitter	SLX4 Bodypack Transmitter
SLX4 Receiver Rear		
SLX4L Receiver Rear		

Wireless Boundary Microphone	Gooseneck Microphone with Wireless Desktop Base
MX690	MX405 & MX410
MX690	MX405 & MX410
Operating Range: 30 m (100 ft.) Note: Actual range depends on RF signal absorption, reflection, and interference	Type: Condenser (electret bias)
Type: Condenser (electret bias)	Polar Pattern: MX405/C, MX410/C: Cardioid MX405/S, MX410/S: Supercardioid
Polar Pattern (at 1 kHz): Cardioid	Weight: Net MX405: 54 g (1.9 oz) Net MX410: 68 g (2.3 oz)
Power Requirements: 2 “AA” size alkaline or rechargeable batteries	Dimensions: MX405: 152mm L x 7.5mm dia. MX410: 251 mm L x 7.5 mm dia.
Battery Life: ≥8 hours (alkaline)	Weight: Net: 318 g (11.2 oz) Packaged: 516 g (18.2 oz)
Dimensions: 43 mm H x 87 mm W x 148 mm D	Dimensions: 43 mm H x 87 mm W x 148 mm D
Weight: Net: 318 g (11.2 oz) Packaged: 516 g (18.2 oz)	Dimensions: 43 mm H x 87 mm W x 148 mm D

SHURE
LEGENDARY
PERFORMANCE™

United States, Canada,
Latin America, Caribbean:
Shure Incorporated
5800 West Touhy Avenue
Niles, IL 60714-4608 USA

Phone: +1 847-600-2000
Fax: +1 847-600-1212 (USA)
Fax: +1 847-600-6446
Email: info@shure.com
www.shure.com

Europe, Middle East, Africa:
Shure Europe GmbH
Jakob-Dieffenbacher-Str. 12,
75031 Eppingen, Germany

Phone: +49-7262-92490
Fax: +49-7262-9249114
Email: info@shure.de
www.shure.eu

Asia, Pacific:
Shure Asia Limited
22/F, 625 King's Road
North Point, Island East
Hong Kong

Phone: +852-2893-4290
Fax: +852-2893-4055
Email: info@shure.com.hk
www.shureasia.com