



dm20m

20-CHANNELS DIGITAL MIXER



Product Description

It has two USB interfaces for recording, playback, scene memory, WIFI connection. 20 inputs including 12 pro mic and 2 stereo, professional digital signal input port, 8 BUSSES including 8 assignable analog and digital output ports.

Furthermore, a 7" Android-powered HD touch screen for WIFI wireless control and nine 100mm electric faders are used to adjust parameters for intuitive operation.

This is a full-function compact digital mixer from Soundking that features premium hardware, touch operation, iPad remote control, the 4th generation SHARC floating point processor, 24bit/192kHz, AD/DA conversion, 8 effect modules, reverb, delay, modulation, GEQ.



Feature

- 8 buses
- 2 USB ports
- Scene memory
- 7" Touch screen
- iPad remote control
- Fourth-generation 40-bit SHARC processor
- DSP with built-in 8 effects, REVERB, DELAY, GEQ, etc.

Application: Recording studio, Live performance, Conference hall, Pub, TV station, Band, etc.

Supports control via Wi-Fi.

with the application on iPad



DM20 remote App



Specifications

Model:	DM 20M	Type:	DIGITAL MIXER
Number of Interface Input:	20	BUS:	8
DSP:	YES	Gain:	YES
Multitrack-Recording:	NO	USB/SD Direct Recording:	YES
USB Play:	YES	Bluetooth Play:	NO
Remote Control:	YES	Touch Screen:	YES
Number of Mono Ins:	16	Number of Stereo Ins:	2
Local MIC IN :	XLR x8 + Combo x4	Local LINE IN :	TRS (x4)
Local Output :	XLR (x8)	Number of Stereo S/PDIF Connectors:	1
Number of Stereo AES/EBU Connectors:	1	Number of Headphone Connectors:	1
Phantom Power:	48V	19" Rackmount:	YES
Height in mm:	100 mm	Width in mm:	325 mm
Depth in mm:	445 mm	Weight in kg:	5.3 kg