

DESCRIPTION


The MX-113-AS is a desk mount (1 unit size) pre-amplifier mixer that comes with 6 microphone inputs, 4 AUX inputs and 2 monaural output. The microphone 1 to 5 inputs have a signal noise gate circuit that allows a signal to pass through only when it is above a set threshold. It can be mounted in an EIA rack with an optional rack mounting bracket (1U size).

SPECIFICATIONS

\* 0dB = 1V

|                    |   |
|--------------------|---|
| Power Source       | 220 - 240 V AC, 50/60 Hz  |
| Power Consumption  | 4 W   |
| Input              | Mic 1-5 : 600Ω, -62 dB*, unbalanced, phone jack (voice switch OFF)<br>600Ω, -54 dB*, unbalanced, phone jack (voice switch ON)<br>(option IT-450 balance transformer)<br>Mic 6 : 600Ω, -62 dB*, unbalanced, phone jack<br>AUX 1 : 10 KΩ, -12 dB*, unbalanced, phone jack/RCA jack<br>(Microphone 6 and AUX 1 are switch type)<br>AUX 2, 3 : 10KΩ, -12 dB*, unbalanced, phone jack/RCA jack<br>AUX 4 : 600Ω, -12 dB*, unbalanced, phone jack<br>(option IT-450 balance transformer) |
| Output             | Line output : 600Ω, 0 dB*, balanced, phone jack<br>Record out : 1 KΩ, 0 dB*, unbalanced, RCA jack   |
| Remote Terminal    | Withstand voltage : DC 30V, Current : 1 A, M3 Screw terminal, 6.4mm   |
| T.H.D              | 1 % or less (1 kHz, rated output)   |
| Frequency Response | 30 Hz - 20 kHz  |
| Noise Level        | 60 dB   |
| Finish             | Front Panel : Aluminum, Black, Paint  |
| Dimensions         | 420 (W) X 50 (H) X 271 (D) mm   |
| Weight             | 3.2 kg  |
| Accessory          | Power Cable (2 pin)   |
| Option             | Rack mount bracket : MB-15B, balanced transformer : IT-450  |

APPEARANCE



UNIT: mm SCALE:1/3