

# LBB 1957/00 Plena Voice Alarm Keypad

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Seven zone selection keys
- ▶ LED indications for zone selection
- ▶ Up to eight keypads can be connected together

The LBB 1957/00 Call Station Keypad is an extension to the LBB 1956/00 Plena Voice Alarm System Call Station that adds seven additional zone-select keys. It has the same stable metal base as the call station. In addition to tabletop use, the special design allows it to be neatly flush-mounted in desktops.

## Functions

Each call station supports six zone selections. Connecting one of these keypads, adds seven zones or zone groups that can be selected. Up to eight keypads can be added to an LBB 1956/00 call station. LEDs on the keypad indicate the active zones.

### Controls and indicators

- Seven zone selection keys
- Seven zone selection LEDs
- Eight DIP switches

### Interconnections

- Two RJ45 jacks
- 24 VDC input
- Keypad connector

## Certifications and approvals

Safety	acc. to EN 60065
Immunity	acc. to EN 55103-2
Emission	acc. to EN 55103-1

## Region Certification

Europe	CE	Declaration of Conformity
--------	----	---------------------------

## Parts included

Quantity	Components
1	LBB 1957/00 Call Station Keypad

## Technical specifications

### Electrical

Power Supply	
Voltage range	24 VDC supplied by LBB 1956/00
Current consumption	<15 mA

**Mechanical**

Base dimensions	40 x 100 x 235 mm (1.57 x 3.97 x 9.25 in)
Weight	Approx. 1 kg
Mounting	Bracket coupled with LBB 1956/00 or other LBB 1957/00
Color	Charcoal with silver

**Environmental**

Operating temperature	-10 °C to +45 °C (14 °F to +113 °F)
Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Relative humidity	<95%

**Ordering information****LBB 1957/00 Plena Voice Alarm Keypad**

An extension to the LBB 1956/00 Plena Voice Alarm System Call Station that adds seven additional zone-select keys.

Order number **LBB1957/00**

**Represented by:****Americas:**

Bosch Security Systems, Inc.  
12000 Portland Avenue South  
Burnsville MN 55337, USA  
Phone: +1-800-392-3497  
Fax: +1-800-955-6831  
audiosupport@us.bosch.com  
www.boschsecurity.com

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com