



**CVE** SERIES  
POWERED LOUDSPEAKERS

# CVE SERIES

## POWERED LOUDSPEAKERS

Even though the CVE series is driven by advanced DSP and loaded with technology, the simplified yet effective control panel allows for quick, efficient setup. There is no complicated display, dial-knob or endless menus to scroll through. Just access all controls with the push of a button to tailor your sound to the environment and your taste. Stream audio from any smartphone or tablet via Bluetooth, in mono or stereo paired mode. The CVE Series is ideal for gigs where portability is paramount, or a lightweight, integrated audio solution is essential. With 3 full-range Polymer enclosure tops and one 18" Plywood subwoofer, the 1000 Watt Class D Amplifier delivers professional, accurate sound with exceptional clarity, wide dispersion, rich bass, and plenty of headroom when the party gets hot. Listen for yourself to Cerwin Vega's 65 years of experience.

### KEY BENEFITS

- 1000 Watt Class D Amplifier for cool, reliable operation
- 5 selectable Sound Settings on all tops to fit any environment
- Thermal protection circuitry keeps you going when the party gets hot
- Universal switching power supply—100/110/240V, 50/60 Hz
- 2-channel Neutrik combo line/mic inputs
- Proprietary CV Loud Limiter to prevent distortion
- Bluetooth™ pairing and wireless linkage
- 90° wide dispersion coverage
- Lightweight, durable cabinets



	<b>CVE-10*</b>	<b>CVE-12*</b>	<b>CVE-15*</b>	<b>CVE-18s*</b>
<b>Power Rating</b>	1000	1000	1000	1000
<b>Amplifier Class</b>	D	D	D	D
<b>Frequency Response (+/- 3dB)</b>	55Hz - 18KHz	52Hz - 18KHz	45Hz - 18KHz	28Hz - 110Hz
<b>Frequency Range (+/- 10dB)</b>	50Hz - 23KHz	44Hz - 23KHz	41Hz - 23KHz	26Hz - 153Hz
<b>Max SPL</b>	124	126	128	126
<b>HF Driver</b>	1"	1"	1"	N/A
<b>LF Driver</b>	10"	12"	15"	18"
<b>Dispersion</b>	90° x 60°	90° x 60°	90° x 60°	N/A
<b>Input/Output</b>	(2) Combo XLR/TRS Inputs (1) XLR Output	(2) Combo XLR/TRS Inputs (1) XLR Output	(2) Combo XLR/TRS Inputs (1) XLR Output	(2) XLR Outputs
<b>Controls</b>	DSP Mode Switch			DSP Mode Switch
	Bluetooth Pair/Link Switch			THRU OUTPUTS Mode Switch
	Channel Volume Knob			Bluetooth Pair/Link Switch
	Bluetooth Volume Knob			Channel Volume Knob
				Bluetooth Volume Knob
<b>Enclosure Construction / Finish</b>	Polymer / Black Textured			18mm Plywood / Black Textured Paint
<b>Switches</b>	EQ Mode Select (5 modes) Bluetooth Pair/Link	EQ Mode Select (5 modes) Bluetooth Pair/Link	EQ Mode Select (5 modes) Bluetooth Pair/Link	EQ Mode Select (2 modes) Bluetooth Pair/Link Output Mode Select
<b>Dimensions (h x w x d)</b>	22" x 13" x 11.3" (559mm x 330mm x 286mm)	24.3" x 14" x 12.5" (616mm x 356mm x 318mm)	27.2" x 16.5" x 15" (692mm x 419mm x 381mm)	24.5" x 21" x 25.5" (622mm x 533mm x 648mm)
<b>Weight (lbs)</b>	29lbs (13.15 Kg)	33lbs (14.96 Kg)	34lbs (15.42 Kg)	66lbs (29.93 Kg)

\*Specifications & appearance subject to change

Contact: 1-800-4GIBSON (1-800-444-2766)

Cerwin-Vega® is a member of the Gibson family of brands

 **CERWIN-VEGA**  
PROFESSIONAL AUDIO