

LS7200 3D Soundbar System



Elegance. Immersion. It's Object Audio Made Simple.

The LS7200's low-profile form contains a multi-driver array fed by a slim external amp connected via a single cable, reproducing Dolby Atmos[®] and DTS:X[®] soundtracks with conviction. Effects move from channel to channel, immersing you in multidimensional sound, while music streamed via Chromecast built-in^{*}, AirPlay, or DTS Play-Fi^{®+} over Wi-Fi[®] has substance that others can't match. Players connect to the receiver's four HDMI[®] inputs, and wiring is concealed for a near-invisible install. With multi-room audio distribution to any component or speaker supporting Chromecast built-in, DTS Play-Fi[®], or FlareConnect^{™+}, LS7200 tailors entertainment around your lifestyle. * Enabled with a firmware update.

HT-L05 5-Channel Network Receiver

- Dolby Atmos® and DTS:X® Object-based Audio Playback for an Immersive Multidimensional Listening Experience
- Discrete Dialog Control Technology for DTS:X
 DTS Neural X[™] Useria interference And Multiple and A
- DTS Neural:X[™] Upmixing for Standard Multichannel Audio Formats
- New Surround Enhancer Mode Based on Dolby[®] Technology
- Dual-band 5 GHz/2.4 GHz Wi-Fi for Stable Network
 Connection
- Ready for Onkyo Controller App*¹ Integrated Multi-room Intuitive Operation
- Features Chromecast built-in^{*2} Wireless Audio Streaming Platform
- DTS Play-Fi^{#2} Shares Music from Onkyo Music Control App to Receiver and Wireless Speakers
- AirPlay Audio Streaming from iTunes and iPad, iPhone, and iPod touch
 Supports Spotify®, TIDAL, TuneIn, and Deezer*3
- Supports Spotify[®], TIDAL, TuneIn, and Deezer^{#3}
 Restanting Maintain Tracking Lange (Version 4.1)
- Bluetooth® Wireless Streaming Technology (Version 4.1+LE)

- 5-Channel Digital Amplification System for Powerful 50 W/Ch Performance (4 Ω, 1 kHz, 1% THD, 1 Channel Driven, IEC)
- 4 HDMI® Inputs / I Output (with ARC/CEC Multilink Control) Supporting 4K/60p, HDCP 2.2, HDR10, and BT.2020
- AccuEQ Room Acoustic Calibration for Balanced Soundfield (Setup Mic Included)
- FlareConnect^{™#2} Multi-room Audio Distribution to Compatible Components and Speakers
- DSD Decoding^{*4} (2. I-Channel/5.6 MHz, Multichannel 2.8 MHz) via Network, HDMI, and USB
- 2.8 MHz) via Network, HDMI, and USB • Assignable Digital Audio Input (Optical) and
- Analog RCA Input • 1080p Video Upscaling to 4K Resolution
- I080p Video Upscaling to 4K Resolution
 FM Tuner with 40-Station Memory Preset

CinemaFILTER[™] Audio Mode

- IM Juner with 40-Station Memory Preset
 USB Type-A Input for USB Memory Audio Playback
- Osb Type-A Input for Osb Plemory Audio Playback
 Graphical User Interface and Simple Remote Controller
- Tone Control (Bass/Treble) ±10 dB for Front L/R Channels • A/V Sync Function (-100 to 500 ms at 48 kHz in 5 ms Steps)

Multiple Listening Enhancement Modes to Suit Content

- LB-403 Soundbar System
- Ultra-low-profile Design for Unobstructed Vision
 Dual-driver System for L/R Channels, Dual Center
 Drivers, and Discrete Height Speakers Enabling
 Object-based Surround-Sound
- Multichannel Audio Cable for Soundbar Connection
 Solid Build Quality, Chic Style, and Excellent Finish
- SLW-403 Wireless Powered Subwoofer
- Powered Bass Reflex Design
- Rated Output Power: 50 W (4 Ω, 100 Hz, 1%, IEC)
 16 cm Cone Woofer
- Sculpted Feet and Quality Finish

*I For IOS and Android[®] devices. Please check App Store or Google Play for device and OS requirements. *2 Enabled with a firmware update. *3 Service availability may vary with region. Please confirm before purchase. Subscription may also be required. *4 DSD not supported over wireless LAN.



LS7200 3D Soundbar System

Dolby Atmos® and DTS:X® Object-based Audio

DTS:X and Dolby Atmos are not mere improvements to existing formats; they've revolutionized sound mixing. Free from the channel bed, sound comes from all directions, even above, with angled drivers bouncing effects off the ceiling and into the audience. No extra speakers or cables required: just authentic and immersive sound from all around.

Wide Choice of Listening Modes

A suite of advanced sound programs are on hand including new Surround Enhancer, a listening mode based on Dolby technology, which wraps sound around the audience by means of virtual rear speakers. DTS Neural: $X^{\scriptscriptstyle M}$, meanwhile, upmixes multichannel formats to 3D audio, while a variety of DSP programs tweak audio response to best suit music, movies, and games.

Music Made Easy with Chromecast built-in*

Stream any music from your smartphone, laptop, or PC to the LS7200 with ease. Control playback with Chromecastenabled apps you know and love from your iPhone, iPad, Android[™] phone or tablet,

Mac or Windows® laptop, or Chromebook.

* Enabled with firmware update

Ready for DTS Play-Fi®* Multi-room Audio

DTS Play-Fi allows you to enjoy high-quality music from connected online services, networked media servers, and your device library over Wi-Fi® to any number of compatible products using the Onkyo Music Control App for iPad, iPhone, and Android™ smartphones/tablets. DTS Play-Fi can synchronize the music in every room. Each member of your family can use their own device to listen to their own music

5.

in their room or group of rooms. DTS Play-Fi lets you easily structure a comprehensive multi-room ecosystem that satisfies virtually any need. For more information, visit www.play-fi.com. * Enabled with a firmware update



ONKYC

Chromecast

built-in

Life's Easy with Onkyo Controller

Our free app collects next-gen network functionalities, including streaming services and network audio, into an intuitive control interface. Perform general operations or send music to compatible speakers from your phone

Internet Radio and On-demand Streaming

TIDAL, Deezer, and TuneIn are baked into the GUI, which makes it super easy to select music using Onkyo Controller or the included remote. Spotify® subscribers can also cast direct from Spotify app to soundbar.



Clean and Simple Connection

How do we send five audio channels to the soundbar without a tangle of wires? Simple: signals pass through a pin-type Multichannel Audio Cable. Plug your players into the receiver, link to the TV with a single HDMI®, and let simplified installation enhance sound with a cleaner look

FlareConnect[™] Wireless Multi-room Audio

FlareConnect* shares audio from network and external audio input sources between compatible components. Enjoy effortless multi-room playback of LP records, CDs, network music services, and more with supported components and speaker systems. Music selection, speaker grouping, and playback management across the home are built into the Onkyo Controller app**.

f-lare connect

* Sharing audio from external inputs is enabled with a future firmware update. External audio inputs supporting FlareConnect may differ depending on model. Please consult individual praduct specifications for more information. ** Download free from the App Store or Google Play.

AccuEQ Room Acoustic Calibration

In moments, AccuEO measures and analyzes sound output from your speakers and performs corrections for beautifully clear and cohesive object audio in your listening space.

Powerful Amps for Moving Sound

The receiver's slim form contains an efficient digital amplification system with independent power supply to deliver loads of clean power to the soundbar. Wireless sub has its own 50 W amp for deep LFEs in movies and games.

Multi-Driver Soundbar System

Pairs of drivers are featured on the left, right, and center channels, while separate woofers reproduce height effects. Despite a slim profile of only 53 mm*, the multi-driver system delivers confident and cinematic sound with a clear view of the screen. * Excluding protruding parts.

Wi-Fi®, AirPlay, and Bluetooth® Technology

Dual-band 5 GHz/2.4 GHz Wi-Fi assures a stable connection so you can stream over AirPlay and the local network. Bluetooth wireless technology provides a quick and simple streaming from your choice of app and device.





SPECIFICATIONS		
5-Channel Network Receiver (HT-L05)		
Amplifier Section		
Power Output	50 W/Ch	
•	(4 Ω, 1 kHz, 1%, 1 Channel Driven, IEC)	
Input Sensitivity and Imp		
	200 mV/47 k Ω (Line)	
Tone Control	±10 dB, 90 Hz (Bass)	
Signal-to-Noise Ratio	80 dB (Line, SP out)	
Signal-co-recise reacto		
Tuner Section		
Tuning Frequency Range	FM 87.5 MHz-108 MHz	
FM Preset Memory	40 Stations	
•••••••••••••••••••••••••••••••••••••••	•••••••••••••••••••••••••••••••••••••••	
General		
Power Supply	AC 100–240 V~, 50/60 Hz	
Power Consumption	60 W	
Standby Power Consump	otion	
, ,	0.38 W (Standby), 2.0 W (Network Standby)	
Dimensions (W x H x D) 435 × 70 × 325.5 mm	
Weight	40 kg	
	1.0 Kg	
SPEAKER SYSTE	M	
Soundbar System	(LB-403)	
Speaker Type	Acoustic Suspension	
Front	(W x H): 70 mm x 40 mm Cone x 4	
Center	(W x H): 70 mm x 40 mm Cone x 2	
Height:	58 mm Cone x 2	
Frequency Response	100 Hz-20 kHz	
Output Sound Pressure I		
ouput bound i ressure i	78 dB/W/m (L/C/R), 78.6 dB/W/m (TL/TR)	
Nominal Impedance	4 Ω	
- tominar inspectance		
General		
Dimensions (W x H x D) 950 x 55 x 80 mm	
Weight	2.3 kg	
	- 0	
Subwoofer (SLW-4	403)	
Speaker Type	Active, Bass Reflex	
Driver	16 cm Cone	

Speaker type	7 YEAVE, DUDD THENEX
Driver	16 cm Cone
Frequency Response	30–200 Hz
Rated Output Power	50 W (4 Ω, 100 Hz, 1%)
Output Sound Pressure Level	
	90 dB/W/m
Power Consumption	15 W
Standby Power Consumption	
	0.32 W
General	
Dimensions (W x H x D) 261 x 338 x 269 mm
Weight	6.2 kg

CARTON

Dimensions (W x H x D) 1,098 x 354 x 518 mm Weight 18.0 kg

Supplied Accessories

 Soundbar connection cable • Speaker setup microphone
 FM wire antenna • Quick Start Guide • Remote controller
 •AAA (R03) batteries x 2 • Power cord for SLW-403 Non-skid pads x 4



HT-L05 Rear View

Text on receiver may vary with region

Due to a policy of continuous product improvement. Onlyo reserves the right to change specifications and appearance without notice. Manufactured under license from Dobly Laboratories. Dobly, Dobly Atmos, Dobly TueHD, Dobly Digtal Dus, and the double-D symbol are trademarks of Dobly Laboratories. For DTS patents, see http://patents.dts.com. Manufactured under license from DTS. Inc. DTS inc policy. DTS in combination with the Symbol, DTSX. DTS NucuraX. Play-FLDTS-HD logos, and DTS-HD Master Audio are registered trademarks of Dobly. Laboratories. For DTS patents, see http://patents.dts.com.Planufactured under license from DTS. Inc. DTS inc symbol, DTS inc. DTS inc. DTS inc. DTS inc. All Rights Reserved. HDMI, the HDMI logo, and High-Definition Multimedia Interface are trademarks or registered trademarks of HDM are trademarks of Apple Inc., registered in the US. and other countries. Made for iPdG⁻, "Thade for iPdG

